

## esserbus transponder 12 relays (8 bit)



### Part-No. 808610.10

Approval: VdS, CNBOP, BOSEC

The esserbus transponder works as a loop device on the multi-functional primary line. With the 12 relays module, it is possible to expand the number of exits per control unit. Depending on the control unit, it can be integrated or used with fire detectors in mixed operation. The esserbus transponder can be optionally extended by adding the additional isolator board Part No. 788612. esserbus transponder voltage supply: via the multi-functional primary line. The esserbus transponder can be wired with an external switching voltage of 12V DC or 24V DC for the K1 to K12 relays. The external voltage supply of the transponder can be programmed to be monitored in the customer data in the operating mode. In the "floating" operating mode, no external switching voltage of the relays is necessary. 11 relays are freely programmable. The maximum line length from the transponder to the external device is up to 1000 m.

#### Features:

- Only one loop address is needed per transponder
- Max. 100 transponders per FACP
- Max. 32 transponders per loop
- Max. 32 transponders per detector zone

Operating voltage	10 ... 28 V DC
Current consumption @ 12 V DC	approx. 3 mA
Quiescent current @ 19 V DC	250 µA
Contact load relay	30 V DC / 1 A (max. 3 A each transponder)
Ambient temperature	-10 °C ... 50 °C
Storage temperature	-25 °C ... 75 °C
Type of protection	IP 40 (with housing)
Air humidity	< 95 % (non condensing)
Weight	approx. 110 g
Dimensions	W: 150 mm H: 82 mm D: 20 mm

#### Accessories:

788612	Loop isolator PCB
788600	Surface mounting housing gray, similar to RAL 7035
788650.10	Surface mounting housing white, similar to RAL 9003
788601	Flush mounting housing gray, similar to RAL 7035
788651.10	Flush mounting housing white, similar to RAL 9003